



3 IN1 CURRENT TRANSFORMER

- Split Core
- Primary input 100A~5000A
- Secondary output 5A/1A
- Two building fixing methods: base, busbar mounting.
- Wide inner window, allowing clamping of big cables or bus-bars



Ration (A)	BURDNRN (VA)	
	CLASS 0.5	CLASS 1.0
100/5	1.5	2.5
150/5	1.5	2.5
200/5	2.5	3.75
250/5	2.5	5
300/5	5	5
400/5	5	5
250/5	1.5	2.5
300/5	2.5	5
400/5	3.75	5
500/5	5	7.5
600/5	5	7.5
750/5	5	10
800/5	5	10
1000/5	7.5	10
500/5	2.5	5
600/5	2.5	5
750/5	5	10
800/5	5	10
1000/5	7.5	10
1200/5	7.5	10
1250/5	7.5	10
1500/5	7.5	10
1000/5	10	15
1500/5	10	15
2000/5	15	20
2500/5	20	25
3000/5	20	30
4000/5	20	30
5000/5	20	30
6000/5	20	30

SPECIFICATION	
Frequency	50Hz-60Hz
Rated Current	100A to 5000A loads
Rated Output	5A / 1A (AC)
Accuracy	Class 0.5 or 1 from 20% to 120% of rated current
Phase Angle	less than 2 degrees at 50% of rated current
Insulation Voltage	600Vac
Maximum Primary	5000Vac (Insulated Conductor)
Dielectric Strength	2.5 kV / 1 mA / 1 min
Operating Temperature	-15°C to 60°C
Operating Humidity	<85%
Case Material	PC / UL 94-V0
Bobbin	PBT
Internal Structure	Epoxy

DIMENSIONS

